

8-Port Antenna 698-960 | 1427-2690 | 1427-2690 | 1427-2690 MHz

65° 2696 mm

LTE Ready

UltraLine

6890400N

6890400NG 6890400NDx

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

- Quad band antenna, dual polarisation, 8 connectors
- Independent tilt on each band 2-12° / 2-12° / 2-12°
- UltraLine platform with multi-array capability
- MET and RET versions, 3GPP/AISG2.0, in multiple single RET (multiple device type1) or in Multi-RET (device type 17, with firmware above MD3.10).
- Our patented, RET module controlling all tilt angles, fully inserted inside the antenna (field replaceable)

	Frequency Range (MHz)	698-960	1427-2690	1427-2690	1427-2690	NO
RODUCT OVERVIEW	Array	R 1	Y 1	Y2	Y 3	
	Connector	1-2	3-4	5-6	7-8	COMING
	Polarization	XPOL	XPOL	XPOL	XPOL	SOON
	Azimuth Beamwidth (avg)	65°	65°	65°	65°	
P	Electrical Downtilt	2-12°	2-12°	2-12°	2-12°	
	Dimensions		2696 x 305	5 x 162 mm		-

ORDERING OPTIONS Select from the different options listed below

SELECT ELECTRICAL DOWNTILT SELECT CONTROL & AISG PROTOCOL ACTUATOR		SELECT CONNECTOR TYPE	ANTENNA MODEL NUMBER
Manual Electrical Tilt (MET)		4.3-10 Female	6890400N
Remote Electrical Tilt (RET)	Multi-Device Control Unit (MDCU)	4.3-10 Female	6890400NG
AISG v2.0 / 3GPP	Multi-Device Dual Unit (MDDU)	4.3-10 Female	6890400NDx*

*Pre-commissioned configuration; Contact Amphenol for further details.





6890400N

6890400NG 6890400NDx

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ELECTRICAL SPECIFICATIONS Ultra Low Band									
Frequency Range		MHz	698-960						
		MHz	698-806	790-862	824-894	880-960			
Polarization				±	:45°				
Gain	Over all Tilts	dBi	15.5	16.0	16.2	16.7			
Azimuth Beamwidth		degrees	71.5°	67.7°	67.3°	66.0°			
Elevation Beamwidth		degrees	8.6°	7.7°	7.4°	6.9°			
Electrical Downtilt		degrees	2°-12°						
Impedance		Ohms	50						
VSWR			< 1.5						
Passive Interr 3rd Order for	nodulation 2 x 20W Carriers	dBc		<	-153				
Front-to-Back	c Ratio, Total Power, ±30°	dB	> 27.5	> 27.5	> 27.5	> 27.5			
Upper Sidelobe Suppression, Peak to 20°		dB	> 14.0	> 14.0	> 14.0	> 14.0			
Maximum Effective Power Per Port		Watts		25	50 W	I			
Inter/Intra Band Isolation		dB		>	25				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

Y1

Frequency Range	MHz		1427-2690						
	MHz	1427-1518	1695-1880	1850-1990	1920-2180	2300-2500	2490-2690		
Polarization			±45°						
Gain Over all Tilts	dBi	15.7	16.3	16.5	16.9	16.2	16.8		
Azimuth Beamwidth	degrees	67.0°	70.3°	65.9°	62.7°	66.2°	58°		
Elevation Beamwidth	degrees	8.7°	7.1°	6.7°	6.2°	5.4°	4.9°		
Electrical Downtilt	degrees	2°-12°							
Impedance	Ohms	50							
VSWR		< 1.5							
Passive Intermodulation 3rd Order for 2 x 20W Carriers	dBc	< -153							
Front-to-Back Ratio, Total Power, ±30°	dB	> 27.5	> 27.5	> 27.5	> 27.5	> 27.5	> 27.5		
Upper Sidelobe Suppression, Peak to 20°	dB	> 14.0	> 14.0	> 14.0	> 14.0	> 14.0	> 14.0		
Maximum Effective Power Per Port Watts		200 W							
Inter/Intra Band Isolation	dB			> 2	25				

ELECTRICAL SPECIFICATIONS MEGA Wide Band

Standard values based on NGMN-P-BASTA version 9.6 recommendation.



6890400N

6890400NG 6890400NDx

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ELECTRICA	L SPECIFICATIONS MEG	<mark> </mark>								
Frequency Range N		MHz		1427-2690						
		MHz	1427-1518	1695-1880	1850-1990	1920-2180	2300-2500	2490-2690		
Polarization				1	±2	15°				
Gain	Over all Tilts	dBi	15.7	16.3	16.5	16.9	16.2	16.8		
Azimuth Beamwidth		degrees	67.0°	70.3°	65.9°	62.7°	66.2°	58°		
Elevation Beamwidth		degrees	8.7°	7.1°	6.7°	6.2°	5.4°	4.9°		
Electrical Downtilt de			2°-12°							
Impedance	ice Ohms 50									
VSWR			< 1.5							
Passive Interr 3rd Order for	nodulation 2 x 20W Carriers	dBc			< -	153				
Front-to-Back	k Ratio, Total Power, ±30°	dB	> 27.5	> 27.5	> 27.5	> 27.5	> 27.5	> 27.5		
Upper Sidelobe Suppression, Peak to 20°		dB	> 14.0	> 14.0	> 14.0	> 14.0	> 14.0	> 14.0		
Maximum Effective Power Per Port Wat		Watts			200) W				
Inter/Intra Band Isolation		dB			>	25				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

							Dito in the store is a			
ELECTRICAL SPECIFICATIONS MEGA Wide Band										
Frequency F	Range	MHz		1427-2690						
		MHz	1427-1518	1695-1880	1850-1990	1920-2180	2300-2500	2490-2690		
Polarization				±45°						
Gain	Over all Tilts	dBi	15.7	16.3	16.5	16.9	16.2	16.8		
Azimuth Beamwidth		degrees	67.0°	70.3°	65.9°	62.7°	66.2°	58°		
Elevation Beamwidth		degrees	8.7°	7.1°	6.7°	6.2°	5.4°	4.9°		
Electrical Do	owntilt	degrees			2°-	12°		·		
Impedance	*	Ohms			5	0				
VSWR					< 1	1.5				
Passive Inter 3rd Order fo	rmodulation or 2 x 20W Carriers	dBc			< -	153				
Front-to-Bac	ck Ratio, Total Power, ±30°	dB	> 27.5	> 27.5	> 27.5	> 27.5	> 27.5	> 27.5		
Upper Sidel	obe Suppression, Peak to 20°	dB	> 14.0	> 14.0	> 14.0	> 14.0	> 14.0	> 14.0		
Maximum E	ffective Power Per Port	Watts	200 W							
Inter/Intra Band Isolation dB			> 25							

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

Quoted performance parameters are provided to offer typical, peak or range values only and may vary as a result of normal testing, manufacturing and operational conditions. Extreme operational conditions and/or stress on structural supports is beyond our control. Such conditions may result in damage to this product. Improvements to products may be made without notice.

CONNECTING PEOPLE + TECHNOLOGY www.amphenol-antennas.com



6890400N

6890400NG 6890400NDx 4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ELECTRICAL DOWNTILT CONTROL

For multiband antennas, electrical downtilt for each band can be controlled separately.					
Manual Electrical Tilt (MET) Control	A colored knob at the end of the tilt indicator allows change of the tilt without need of a tool. The knob color is identical to the corresponding connector color. The manual tilt 'override' function is always available with no need to remove the physical RET motor.				
Remote Electrical Tilt (RET) Control	The remote control of the electrical tilt is managed by a Multi-Device Control Unit (MDCU) or a Multi-Device Dual Unit (MDDU) inserted in the bottom of the antenna. See details below and refer to the ordering options to see which actuators are available with this particular antenna. A single actuator individually controls the tilt of each band (no need for daisy chain cables between the bands). This module does not add any additional length to the antenna.				

RET ACTUATOR

Amphenol's **RET-READY** antennas are delivered with the RET Actuator already installed and pre-commissioned with all antenna parameters. Every RET device is factory configured and calibrated so the antenna is ready to be used once delivered to the site which means that there is no need for further installation of RET devices or for programming their configuration or for running a calibration process.

 RET-READY ACTUATORS
 Multi-Device Control Unit (MDCU). The MCDU is an electronic module that allows the remote control of the electrical downtilt (RET) in Amphenol antennas with factory embedded motors. The MDCU is factory installed and has two male AISG 8 pin connectors (type IEC60130-9 Ed 3.0). Refer to the ORDERING OPTIONS for availability with this model

 Multi-Device Dual Unit (MDDU). The MDDU allows two separate RET Controllers to independently drive the RETs in antennas with

Multi-Device Dual Unit (MDDU). The MDDU allows two separate RET Controllers to independently drive the RETs in antennas with factory embedded motors (for antenna sharing or two technologies). The MDDU is factory installed and has one pair of AISG Male and Female connectors (type IEC60130-9). *Refer to the* ORDERING OPTIONS for availability with this model.

Number of RET-READY	Actuators	One per antenna			
Input Voltage		+10 to +30 V			
Power Consumption	Idle State (AISG P1)	0.5 W			
	High Power Mode (AISG P2)	3 W			
Protocol		3GPP/AISG 2.0			
Tilt Change Duration		Less than 15 seconds, typical (may vary dependent on antenna type and outdoor temperature)			
Precision		±0.5°			
Tilt Change Capability		50,000 minimum			
Field Replaceable Unit		Yes			



6890400N

6890400NG 6890400NDx 4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm





_	ARRAY	FREQUENCY	CONNECTOR	CONNECTOR TYPE
You ⁻	R 1	698-960	1-2	4.3-10 Female
Y LA	<mark>_</mark> Y1	1427-2690	3-4	4.3-10 Female
RRA	Y2	1427-2690	5-6	4.3-10 Female
٩	<mark>_</mark> Y3	1427-2690	7-8	4.3-10 Female

Diagram shown at right depicts the view from the front of the antenna. The illustration is not shown to scale.

The illustration is not shown to sca

MECHANICAL SPECIFICATIONS

Length	1		mm (in)	2696 (106.1)
Width		mm (in)	305 (12.0)	
Depth			mm (in)	162 (6.4)
Net W	'eight - Antenna <mark>Onl</mark> y		kg (lbs)	33 (72.8)
Mecha	ani cal Dist ance Betwee	en Mounting Points	mm (in)	Refer to Diagram
Windle	bad	Calculation	km/h (mph)	150 (93.2)
		Frontal	N (lbf)	1032 (232.0)
		Lateral	N (lbf)	469 (105.4)
		Rearside	N (lbf)	1011 (227.3)
Operational Wind Speed		km/h (mph)	160 (99.4)	
Surviva	al Wind Speed		km/h (mph)	200 (124)
Radon	ne Color			Gray RAL7035
Radon	ne Material			Outdoor Plastic
Lightning Protection			Direct Ground	
อเ	Shipping Dimensions (Length x Width x Depth)		mm (in)	2950 x 400 x 280 (116.1 x 15.7 x 11.0)
ippir	Shipping Weight		kg (lbs)	44 (97.0)
Sh	Shipping Volume		m ³ (ft ³)	0.243 (8.6)



6890400N

6890400NG 6890400NDx 4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ENVIRONMENTAL SPECIFICATIONS

Environmental Standard		ETS 300 019
Operating Temperature	° C (° F)	-40° to +60° (-40° to 140°)
Product Environmental Compliance		Product is RoHs Compliant

ACCESSORIES All accessories are ordered separately unless otherwise indicated

ITEM	MODEL NUMBER	WEIGHT
Brackets for pole Ø48 to Ø115 mm (Ø1.9 to Ø4.5 in) <i>delivered as standard</i>	0900181/00	3.4 kg (7.5 lbs)
Brackets for pole Ø70 to Ø150 mm (Ø2.8-Ø5.9 in) optional	0900182/00	3.9 kg (8.6 lbs)
Kit to add mechanical tilt (0° to 10°) to above brackets optional	0900397/00	3.0 kg (6.6 lbs)

Wall mounting brackets are available upon request

INSTALLATION Please read all installation notes before installing this product.



Always attach the antenna by all mounting points.

Do not install the antenna with the connectors facing upwards.

NO IMAGE AVAILABLE COMING SOON