

1945 mm

5978600P

5978600PG 5978600PDx

6-Band, 12-Port, 65°, XPOL, Panel Antenna, Variable Tilt, 1945 mm



- Twin tri band antenna, dual polarisation, 12 connectors
- Independent tilt on each band 2-12° / 2-12° / 2-12° / 2-12° / 2-12°
- Lightweight Twin+™, next generation TwinLine™ platform and low windload
- MET and RET versions, 3GPP/AISG2.0, in multiple single RET (multiple device type1) or in Multi-RET (device type 17, with firmware above MD3.10).
- Our patented, RET module controlling all tilt angles, fully inserted inside the antenna (field replaceable)

	Frequency Range (MHz)	698-960	698-960	1427-2180	1427-2180	2490-2690	2490-2690		
>	Array	■ R1	■ R2	■ B1	■ B2	<u>Y</u> 1	Y2		
OVERVIEW	Connector	1-2	3-4	5-6	7-8	9-10	11-12		
	Polarization	XPOL	XPOL	XPOL	XPOL	XPOL	XPOL		
PRODUCT	Azimuth Beamwidth (avg)	65°	65°	65°	65°	65°	65°		
础	Electrical Downtilt	2-12°	2-12°	2-12°	2-12°	2-12°	2-12°		
	Dimensions	1945 x 432 x 175 mm							



ORDERING OPTIONS Select from the different options listed below

SELECT ELECTRICAL DOWNTILT CONTROL & AISG PROTOCOL	SELECT ACTUATOR	SELECT CONNECTOR TYPE	ANTENNA MODEL NUMBER
Manual Electrical Tilt (MET)		4.3-10 Female	5978600P
Remote Electrical Tilt (RET)	Multi-Device Control Unit (MDCU)	4.3-10 Female	5978600PG
AISG v2.0 / 3GPP	Multi-Device Dual Unit (MDDU)	4.3-10 Female	5978600PDx*

^{*}Pre-commissioned configuration; Contact Amphenol for further details.







1945 mm

5978600P

5978600PG 5978600PDx

6-Band, 12-Port, 65°, XPOL, Panel Antenna, Variable Tilt, 1945 mm

ELECTRICAL SPECIFICATIONS Ultra Low Band		■ R1					
Frequency Range		MHz	698-960				
		MHz	698-806	790-862	824-894	880-960	
Polarization			±45°				
Gain	Over all Tilts	dBi	14.1 ± 0.5	14.8 ± 0.4	15.0 ± 0.6	15.4 ± 0.4	
Azimuth Beamwidth		degrees	71.9° ± 2.2°	68.3° ± 3.2°	67.2° ± 2.5°	66.2° ± 2.9°	
Elevation Beamwidth		degrees	12.0° ± 1.1°	10.5° ± 0.7°	10.1° ± 0.3°	9.4° ± 0.9°	
Electrical Downtilt degree			2°-12°				
Impedance Ohms			50				
VSWR				<	1.5		
Passive Interr 3rd Order for	nodulation 2 x 20W Carriers	dBm	< -110				
Front-to-Back	Ratio, Total Power, ±30°	dB	> 24.3	> 23.4	> 23.1	> 23.8	
Upper Sidelok	pe Suppression, Peak to 20°	dB	> 16.5	> 17.8	> 16.9	> 15.3	
Cross Polar	Main Direction (0°)	dB	> 22.7	> 25.2	> 23.1	> 19.0	
Ratio	Sector Edges (±60°)	dB	> 7.0	> 7.3	> 7.0	> 7.0	
Maximum Effective Power Per Port		Watts	250 W				
Inter/Intra Band Isolation		dB	> 25				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

ELECTRICAL SPECIFICATIONS Ultra Low Band

	R2

Frequency Range		MHz		698	-960		
		MHz	698-806	790-862	824-894	880-960	
Polarization			±45°				
Gain	Over all Tilts	dBi	14.1 ± 0.6	14.9 ± 0.5	15.1 ± 0.5	15.4 ± 0.4	
Azimuth Bear	mwidth	degrees	71.9° ± 2.7°	68.5° ± 2.8°	68.2° ± 2.4°	67.6° ± 2.7°	
Elevation Beamwidth		degrees	11.9° ± 1.2°	10.4° ± 0.7°	10.0° ± 0.6°	9.3° ± 0.5°	
Electrical Downtilt		degrees	2°-12°				
Impedance		Ohms	50				
VSWR			< 1.5				
Passive Interr 3rd Order for	modulation · 2 x 20W Carriers	dBm	< -110				
Front-to-Back	Ratio, Total Power, ±30°	dB	> 22.9	> 23.4	> 23.5	> 23.6	
Upper Sidelok	pe Suppression, Peak to 20°	dB	> 17.7	> 18.1	> 19.1	> 16.6	
Cross Polar	Main Direction (0°)	dB	> 18.8	> 21.4	> 19.9	> 17.8	
Ratio	Sector Edges (±60°)	dB	> 6.3	> 6.1	> 6.3	> 5.9	
Maximum Effective Power Per Port		Watts	250 W				
Inter/Intra Band Isolation		dB	> 25				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.



1945 mm

5978600P

5978600PG 5978600PDx

6-Band, 12-Port, 65°, XPOL, Panel Antenna, Variable Tilt, 1945 mm

Frequency Range MHz		1427-2180					
riequency Ra	inge		142 <i>1-</i> 210U				
		MHz	1427-1518	1695-1880	1850-1990	1920-2180	
Polarization			±45°				
Gain	Over all Tilts	dBi	15.5 ± 0.4	16.4 ± 0.5	16.5 ± 0.5	16.8° ± 0.5	
Azimuth Beamwidth		degrees	70.5° ± 2.0°	68.3° ± 3.1°	65.0° ± 2.5°	63.4° ± 2.9°	
Elevation Beamwidth		degrees	8.3° ± 0.4°	6.9° ± 0.5°	6.5° ± 0.4°	6.0° ± 0.7°	
Electrical Downtilt de		degrees	2°-12°				
Impedance Ohms			50				
VSWR			< 1.5				
Passive Interi 3rd Order foi	modulation · 2 x 20W Carriers	dBm	< -110				
Front-to-Bacl	Ratio, Total Power, ±30°	dB	> 25.9	> 28.5	> 31.0	> 29.6	
Upper Sidelol	pe Suppression, Peak to 20°	dB	> 13.3	> 15.6	> 14.7	> 13.4	
Cross Polar	Main Direction (0°)	dB	> 17.5	> 20.0	> 22.3	> 20.9	
Ratio	Sector Edges (±60°)	dB	> 9.1	> 7.1	> 8.9	> 8.2	
Maximum Effective Power Per Port		Watts	200 W				
Inter/Intra Ba	nd Isolation	dB	> 28				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

ELECTRICAL SPECIFICATIONS Filtered Array (Y2)

	R2

Frequency Range		MHz	1427-2180				
		MHz	1427-1518	1695-1880	1850-1990	1920-2180	
Polarization			±45°				
Gain	Over all Tilts	dBi	15.6 ± 0.4	16.4 ± 0.4	16.5 ± 0.5	16.8 ± 0.5	
Azimuth Bear	nwidth	degrees	70.1° ± 2.0°	67.8° ± 2.3°	66.2° ± 2.1°	63.7° ± 3.6°	
Elevation Beamwidth		degrees	8.1° ± 0.5°	6.8° ± 0.4°	6.4° ± 0.4°	5.9° ± 0.7°	
Electrical Downtilt		degrees	2°-12°				
Impedance		Ohms	50				
VSWR			< 1.5				
Passive Interr 3rd Order for	modulation 2 x 20W Carriers	dBm	< -110				
Front-to-Back	Ratio, Total Power, ±30°	dB	> 26.7	> 27.5	> 29.4	> 28.5	
Upper Sidelok	pe Suppression, Peak to 20°	dB	> 13.1	> 16.3	> 15.1	> 14.4	
Cross Polar	Main Direction (0°)	dB	> 19.6	> 19.0	> 19.5	> 17.3	
Ratio	Sector Edges (±60°)	dB	> 8.4	> 7.4	> 9.2	> 8.5	
Maximum Effective Power Per Port		Watts	200 W				
Inter/Intra Band Isolation		dB	> 28				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.



1945 mm

5978600P

5978600PG 5978600PDx

6-Band, 12-Port, 65°, XPOL, Panel Antenna, Variable Tilt, 1945 mm

ELECTRICA	L SPECIFICATIONS Filter	red Array (B1)	□ Y1	
Frequency Ra	Frequency Range		2490-2690	
Polarization			±45°	
Gain	Over all Tilts	dBi	16.8 ± 0.3	
Azimuth Bear	nwidth	degrees	60.8° ± 4.4°	
Elevation Bea	amwidth	degrees	4.7° ± 0.3°	
Electrical Dov	Electrical Downtilt		2°-12°	
Impedance	Impedance		50	
VSWR			< 1.5	
Passive Interr 3rd Order for	nodulation 2 x 20W Carriers	dBm	< -110	
Front-to-Back	Ratio, Total Power, ±30°	dB	> 28.0	
Upper Sidelok	pe Suppression, Peak to 20°	dB	> 13.7	
Cross Polar	, ,		> 16.4	
Ratio Sector Edges (±60°)		dB	> 6.7	
Maximum Eff	Maximum Effective Power Per Port		200 W	
Inter/Intra Ba	nd Isolation	dB	> 25	

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

ELECTRICA	L SPECIFICATIONS Filter	red Array (B2)	<mark>□</mark> Y2
Frequency Ra	ange	MHz	2490-2690
Polarization			±45°
Gain	Over all Tilts	dBi	16.8 ± 0.4
Azimuth Bear	mwidth	degrees	60.9° ± 4.3°
Elevation Bea	amwidth	degrees	4.7° ± 0.3°
Electrical Downtilt		degrees	2°-12°
Impedance	Impedance		50
VSWR			< 1.5
Passive Interr 3rd Order for	modulation · 2 x 20W Carriers	dBm	< -110
Front-to-Back	Ratio, Total Power, ±30°	dB	> 25.5
Upper Sidelok	pe Suppression, Peak to 20°	dB	> 13.4
Cross Polar	Main Direction (0°)	dB	> 15.6
Ratio	Sector Edges (±60°)	dB	> 6.8
Maximum Effective Power Per Port		Watts	200 W
Inter/Intra Ba	nd Isolation	dB	> 25

Standard values based on NGMN-P-BASTA version 9.6 recommendation.



1945 mm

5978600P

5978600PG 5978600PDx

6-Band, 12-Port, 65°, XPOL, Panel Antenna, Variable Tilt, 1945 mm

ELECTRICAL DOWNTILT CONTROL

For multiband antennas, electr	For multiband antennas, electrical downtilt for each band can be controlled separately.					
Manual Electrical Tilt (MET) Control	A colored knob at the end of the tilt indicator allows change of the tilt without need of a tool. The knob color is identical to the corresponding connector color. The manual tilt 'override' function is always available with no need to remove the physical RET motor.					
Remote Electrical Tilt (RET) Control	The remote control of the electrical tilt is managed by a Multi-Device Control Unit (MDCU) or a Multi-Device Dual Unit (MDDU) inserted in the bottom of the antenna. See details below and refer to the ordering options to see which actuators are available with this particular antenna. A single actuator individually controls the tilt of each band (no need for daisy chain cables between the bands). This module does not add any additional length to the antenna.					

RET ACTUATOR

Amphenol's **RET-READY** antennas are delivered with the RET Actuator already installed and pre-commissioned with all antenna parameters. Every RET device is factory configured and calibrated so the antenna is ready to be used once delivered to the site which means that there is no need for further installation of RET devices or for programming their configuration or for running a calibration process.

RET-READY ACTUATORS

Multi-Device Control Unit (MDCU). The MCDU is an electronic module that allows the remote control of the electrical downtilt (RET) in Amphenol antennas with factory embedded motors. The MDCU is factory installed. Refer to the ORDERING OPTIONS for availability with this model.

Multi-Device Dual Unit (MDDU). The MDDU allows two separate RET Controllers to independently drive the RETs in antennas with factory embedded motors (for antenna sharing or two technologies). The MDDU is factory installed. Refer to the ORDERING OPTIONS for availability with this model.

Number of RET-READ	Y Actuators	One per antenna		
Input Voltage		+10 to +30 V		
Power Consumption Idle State (AISG P1)		0.5 W		
	High Power Mode (AISG P2)	3 W		
Protocol		3GPP/AISG 2.0		
Tilt Change Duration		Less than 15 seconds, typical (may vary dependent on antenna type and outdoor temperature)		
Precision		±0.5°		
Tilt Change Capability		50,000 minimum		
MDCU		One pair of AISG Male and Female (type IEC60130-9)		
RET Interface MDDU		Two male AISG 8 pin connectors (type IEC60130-9 Ed 3.0)		
Field Replaceable Unit		Yes		




1945 mm

5978600P

5978600PG 5978600PDx

6-Band, 12-Port, 65°, XPOL, Panel Antenna, Variable Tilt, 1945 mm



ARRAY LAYOUT	ARRAY	FREQUENCY	CONNECTOR	CONNECTOR TYPE	
	■ R1	698-960	1-2	4.3-10 Female	
	■ R2	698-960	3-4	4.3-10 Female	
	■ B1	1427-2180	5-6	4.3-10 Female	
	■ B2	1427-2180	7-8	4.3-10 Female	
	Y1	2490-2690	9-10	4.3-10 Female	
	Y2	2490-2690	11-12	4.3-10 Female	




Diagram shown at right depicts the view from the front of the antenna.

The illustration is not shown to scale.

MECHANICAL SPECIFICATIONS

MEGINATIONE STEEL TOWN TOWN							
Length			1945 (76.6)				
Width			432 (17.0)				
Depth		mm (in)	175 (6.9)				
Net Weight - Antenna Only		kg (lbs)	39 (86.0)				
Mechanical Distance Between Mounting Points		mm (in)	Refer to Diagram				
load 991-1-4:2005 using Tunnel Coefficients)	Calculation	km/h (mph)	150 (93.2)				
	Frontal	N (lbf)	635 (142.8)				
	Lateral	N (lbf)	395 (88.8)				
	Rearside	N (lbf)	656 (147.5)				
Operational Wind Speed		km/h (mph)	160 (99.4)				
Survival Wind Speed			200 (124)				
Radome Color			Gray RAL7035				
Radome Material			Outdoor Fiberglass				
Lightning Protection			Direct Ground				
Shipping Dimensions (Length x Width x Depth)		mm (in)	2150 x 500 x 340 (84.6 x 19.7 x 13.4)				
Shipping Weight		kg (lbs)	50 (110.2)				
Shipping Volume		m³ (ft³)	0.37 (13.1)				
	eight - Antenna Only nical Distance Between and 91-1-4:2005 using Tunnel Coefficients) tional Wind Speed al Wind Speed ale Color ale Material ang Protection Shipping Dimensions Shipping Weight	eight - Antenna Only nical Distance Between Mounting Points ad 91-1-4:2005 using Tunnel Coefficients) Enable Tunnel Wind Speed Tunnel Wi	mm (in) mm (in) mm (in) mm (in) mm (in) kg (lbs) nical Distance Between Mounting Points ad 91-1-4:2005 using Tunnel Coefficients) Frontal Lateral N (lbf) Rearside N (lbf) N (lbf) N (lbf) N (lbf) N (mph) N (lbf) N (mph)				



1945 mm

5978600P

5978600PG 5978600PDx

6-Band, 12-Port, 65°, XPOL, Panel Antenna, Variable Tilt, 1945 mm

ENVIRONMENTAL SPECIFICATIONS

Environmental Standard		ETS 300 019	
Operating Temperature	° C (° F)	-40° to +60° (-40° to 140°)	
Product Environmental Compliance		Product is RoHs Compliant	

ACCESSORIES All accessories are ordered separately unless otherwise indicated

ITEM	MODEL NUMBER	WEIGHT
Brackets for pole Ø48 to Ø115 mm (Ø1.9 to Ø4.5 in) <i>delivered as standard</i>	0900181/00	3.4 kg (7.5 lbs)
Brackets for pole Ø70 to Ø150 mm (Ø2.8-Ø5.9 in) <i>optional</i>	0900182/00	3.9 kg (8.6 lbs)
Kit to add mechanical tilt (0° to 10°) to above brackets <i>optional</i>	0900396/00	2.3 kg (5.1 lbs)

INSTALLATION Please read all installation notes before installing this product.



Always attach the antenna by all mounting points.

Do not install the antenna with the connectors facing upwards.

