

2696 mm

6890300

6890300N 6890300G 6890300NG

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

- Quad band antenna, dual polarisation, 8 connectors
- \bullet Independent tilt on each band 0-10° / 0-12° / 0-12° / 0-10°
- UltraLine platform with multi-array capability
- MET and RET versions, 3GPP/AISG2.0
- Single RET module to control all tilt angles, fully inserted inside the antenna (field replaceable)

	Frequency Range (MHz)	698-960	1695-2690	1695-2690	1695-2690		
>	Array	■ R1	Y1	Y2	Y3		
OVERVIEW	Connector	1-2	3-4	5-6	7-8		
	Polarization	XPOL	XPOL	XPOL	XPOL		
PRODUCT	Azimuth Beamwidth (avg)	65°	65°	65°	65°		
PI	Electrical Downtilt	0-10°	0-12°	0-12°	0-10°		
	Dimensions	2696 x 305 x 162 mm					





ORDERING OPTIONS Select from the different options listed below

SELECT ELECTRICAL DOWNTILT CONTROL & AISG PROTOCOL	SELECT ACTUATOR	SELECT CONNECTOR TYPE	ANTENNA MODEL NUMBER
March J. Floor Co. J. Tily (MAFT)		4.3-10 Female	6890300N
Manual Electrical Tilt (MET)		7/16-DIN Female	6890300
Remote Electrical Tilt (RET)	Multi-Device Control Unit	4.3-10 Female	6890300NG
AISG v2.0 / 3GPP	(MDCU)	7/16-DIN Female	6890300G







2696 mm

6890300

6890300N 6890300G 6890300NG

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ELECTRICA	AL SPECIFICATIONS Lo	w Band			R1		
Frequency Range		MHz	698-960				
		MHz	698-806	880-960			
Polarization				±4	45°	1	
Gain Over all Tilts		dBi	15.3 ± 0.6	15.9 ± 0.5	16.3 ± 0.4	16.7 ± 0.4	
Azimuth Beamwidth		degrees	71.5° ± 2.0°	67.6° ± 2.4°	67.2° ± 1.3°	67.5° ± 2.0°	
Elevation Beamwidth		degrees	8.4° ± 0.6°	7.4° ± 0.5°	7.3° ± 0.4°	6.8° ± 0.4°	
Electrical Do	owntilt	degrees	0°-10°				
Impedance		Ohms	50				
VSWR			< 1.5				
Passive Inter 3rd Order fo	rmodulation or 2 x 20W Carriers	dBm	< -110				
Front-to-Bac	ck Ratio, Total Power, ±30°	dB	> 24.2	> 26.5	> 25.1	> 24.2	
Upper Sidelobe Suppression, Peak to 20°		dB	> 17.0	> 16.0	> 15.6	> 14.8	
Cross Polar Ratio - Main Direction (0°)		dB	> 16.1	> 17.1	> 16.0	> 15.9	
Maximum Effective Power Per Port		Watts	200 W				
Inter/Intra Band Isolation		dB	> 25				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

ELECTRICAL SPECIFICATIONS Ultra Wide Band

	V1

Frequency Range		MHz		1695-2690					
		MHz	1695-1880	1850-1990	1920-2180	2300-2500	2490-2690		
Polarization	1				±45°				
Gain	Over all Tilts	dBi	16.4 ± 0.4	16.5 ± 0.4	16.7 ± 0.4	16.6 ± 0.4	16.8 ± 0.4		
Azimuth Beamwidth		degrees	66.9° ± 4.1°	66.4° ± 3.8°	63.0° ± 4.4°	64.9° ± 3.6°	65.5° ± 4.2°		
Elevation Beamwidth		degrees	7.5° ± 0.6°	7.0° ± 0.4°	6.5° ± 0.6°	5.6° ± 0.1°	5.1° ± 0.4°		
Electrical Downtilt		degrees	0°-12°						
Impedance		Ohms	50						
VSWR			< 1.5						
	ermodulation for 2 x 20W Carriers	dBm	< -110						
Front-to-Ba	ck Ratio, Total Power, ±30°	dB	> 23.4	> 23.0	> 23.3	> 24.6	> 25.3		
Upper Sidelobe Suppression, Peak to 20°		dB	> 16.6	> 16.9	> 16.9	> 16.8	> 16.5		
Cross Polar Ratio - Main Direction (0°)		dB	> 14.6	> 14.6	> 15.1	> 14.9	> 14.9		
Maximum Effective Power Per Port		Watts	200 W						
Inter/Intra Band Isolation		dB			> 25				

Standard values based on NGMN-P-BASTA version 9.6 recommendation.



2696 mm

6890300

6890300N 6890300G 6890300NG

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ELECTRIC	CAL SPECIFICATIONS Ultr	a Wide Band	── Y2					
Frequency Range		MHz		1695-2690				
		MHz	1695-1880	1850-1990	1920-2180	2300-2500	2490-2690	
Polarizatio	on				±45°			
Gain Over all Tilts		dBi	16.5 ± 0.4	16.6 ± 0.5	16.9 ± 0.5	16.9 ± 0.5	16.8 ± 0.4	
Azimuth Beamwidth		degrees	65.6° ± 4.5°	64.5° ± 4.9°	62.1° ± 4.4°	62.6° ± 4.5°	65.9° ± 4.0°	
Elevation Beamwidth		degrees	7.1° ± 0.5°	6.6° ± 0.4°	6.2° ± 0.5°	5.2° ± 0.3°	4.8° ± 0.2°	
Electrical Downtilt		degrees	0°-12°					
Impedance	Impedance		50					
VSWR			< 1.5					
	termodulation for 2 x 20W Carriers	dBm	< -110					
Front-to-B	ack Ratio, Total Power, ±30°	dB	> 23.4	> 23.6	> 24.9	> 25.6	> 25.5	
Upper Sidelobe Suppression, Peak to 20°		dB	> 16.9	> 16.5	> 16.9	> 16.1	> 15.9	
Cross Polar Ratio - Main Direction (0°)		dB	> 14.9	> 15.0	> 15.7	> 14.8	> 15.3	
Maximum Effective Power Per Port V		Watts	200 W					
Inter/Intra	Band Isolation	dB			> 25			

Standard values based on NGMN-P-BASTA version 9.6 recommendation.

ELECTRICAL SPECIFICATIONS Ultra Wide Band

	Va
	Y 3

Frequency Range		MHz			1695-2690			
		MHz	1695-1880	1850-1990	1920-2180	2300-2500	2490-2690	
Polarization	1				±45°		ı	
Gain	Over all Tilts	dBi	17.4 ± 0.4	17.4 ± 0.3	17.5 ± 0.5	17.9 ± 0.3	18.0 ± 0.5	
Azimuth Beamwidth		degrees	63.5° ± 3.9°	62.9° ± 3.5°	60.9° ± 4.2°	64.7° ± 3.4°	61.3° ± 3.7°	
Elevation Beamwidth		degrees	6.0° ± 0.4°	5.5° ± 0.4°	5.1° ± 0.6°	4.4° ± 0.2°	4.1° ± 0.3°	
Electrical Downtilt		degrees	0°-10°					
Impedance		Ohms	50					
VSWR			< 1.5					
	ermodulation for 2 x 20W Carriers	dBm	< -110					
Front-to-Ba	ck Ratio, Total Power, ±30°	dB	> 26.9	> 25.1	> 25.2	> 28.8	> 28.1	
Upper Sidelobe Suppression, Peak to 20°		dB	> 15.8	> 17.1	> 17.2	> 15.6	> 16.2	
Cross Polar Ratio - Main Direction (0°)		dB	> 21.0	> 22.5	> 23.4	> 19.1	> 18.2	
Maximum Effective Power Per Port Wat		Watts	200 W					
Inter/Intra Band Isolation		dB	> 28					

Standard values based on NGMN-P-BASTA version 9.6 recommendation.



2696 mm

6890300

6890300N 6890300G 6890300NG

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ELECTRICAL DOWNTILT CONTROL

For multiband antennas, electr	For multiband antennas, electrical downtilt for each band can be controlled separately. Tilt indicator(s) are covered by removable transparent cap(s).				
Manual Electrical Tilt (MET) Control	A colored knob at the end of the tilt indicator allows change of the tilt without need of a tool. The knob color is identical to the corresponding connector color. To access the knob, remove the cap by turning it counter-clockwise. It is re-installed by opposite rotation. Do not remove the transparent cap(s) from the antenna.				
Remote Electrical Tilt (RET) Control	The remote control of the electrical tilt is managed by a Multi-Device Control Unit (MDCU) or a Multi-Device Dual Unit (MDDU) inserted in the bottom of the antenna. See details below and refer to the ordering options to see which actuators are available with this particular antenna. A single actuator individually controls the tilt of each band (no need for daisy chain cables between the bands). This module does not add any additional length to the antenna. For RET control, the transparent caps must be in place and locked. The tilt angle indicators always remain visible and the antenna still has manual tilt control (manual override). Do not remove the transparent cap(s) from the antenna.				

RET ACTUATOR

Amphenol's **RET-READY** antennas are delivered with the RET Actuator already installed and pre-commissioned with all antenna parameters. Every RET device is factory configured and calibrated so the antenna is ready to be used once delivered to the site which means that there is no need for further installation of RET devices or for programming their configuration or for running a calibration process.

RET-READY ACTUATORS

Multi-Device Control Unit (MDCU). The MCDU is an electronic module that allows the remote control of the electrical downtilt (RET) in Amphenol antennas with factory embedded motors. The MDCU is factory installed. Refer to the ORDERING OPTIONS for availability with this model

Multi-Device Dual Unit (MDDU). The MDDU allows two separate RET Controllers to independently drive the RETs in antennas with factory embedded motors (for antenna sharing or two technologies). The MDDU is factory installed. Refer to the ORDERING OPTIONS for availability with this model.

Number of RET-READY Actuators		One per antenna		
Input Voltage		+10 to +30 V		
Power Consumption Idle State Operating		0.5 W		
		4 W typical / 10 W maximum		
Protocol		3GPP/AISG 2.0		
Tilt Change Duration		Less than 15 seconds, typical (may vary dependent on antenna type and outdoor temperature)		
Precision		±0.5°		
Tilt Change Capability		50,000 minimum		
RET Interface		1 pair of AISG Male and Female (type IEC60130-9)		
Field Replaceable Unit		Yes		



2696 mm

6890300

6890300N 6890300G 6890300NG

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm



	ARRAY	FREQUENCY	CONNECTOR	CONNECTOR TYPE
ARRAY LAYOUT	■ R1	698-960	1-2	4.3-10 Female or 7/16-DIN Female Long Neck
	Y1	1695-2690	3-4	4.3-10 Female or 7/16-DIN Female Ultra Long Neck
	Y2	1695-2690	5-6	4.3-10 Female or 7/16-DIN Female Long Neck
	Y3	1695-2690	7-8	4.3-10 Female or 7/16-DIN Female Ultra Long Neck






Diagram shown at right depicts the view from the front of the antenna. The illustration is not shown to scale.

MECHANICAL SPECIFICATIONS

Length			mm (in)	2696 (106.1)
Width			mm (in)	305 (12.0)
Depth			mm (in)	162 (6.4)
Net W	eight - Antenna Only		kg (lbs)	33 (72.8)
Mecha	anical Distance Betwee	en Mounting Points	mm (in)	Refer to Diagram
Windle		Calculation	km/h (mph)	150 (93.2)
(Wind	Tunnel Coefficients)	Frontal	N (lbf)	1032 (232.0)
		Lateral	N (lbf)	469 (105.4)
		Rearside	N (lbf)	1011 (227.3)
Opera	tional Wind Speed		km/h (mph)	160 (99.4)
Surviv	al Wind Speed		km/h (mph)	200 (124)
Radon	ne Color			Gray RAL7035
Radon	ne Material			Outdoor Plastic
Lightning Protection			Direct Ground	
Shipping	Shipping Dimensions (Length x Width x Depth)		mm (in)	2950 × 400 × 280 (116.1 × 15.7 × 11.0)
	Shipping Weight		kg (lbs)	44 (97.0)
	Shipping Volume		m³ (ft³)	0.243 (8.6)



2696 mm

6890300

6890300N 6890300G 6890300NG

4-Band, 8-Port, 65°, XPOL, Panel Antenna, Variable Tilt, UltraLine, 2696 mm

ENVIRONMENTAL SPECIFICATIONS

Environmental Standard		ETS 300 019	
Operating Temperature	° C (° F)	-40° to +60° (-40° to 140°)	
Product Environmental Compliance		Product is RoHs Compliant	

ACCESSORIES All accessories are ordered separately unless otherwise indicated

ITEM	MODEL NUMBER	WEIGHT
Brackets for pole Ø48 to Ø115 mm (Ø1.9 to Ø4.5 in) <i>delivered as standard</i>	0900181/00	3.4 kg (7.5 lbs)
Brackets for pole Ø70 to Ø150 mm (Ø2.8-Ø5.9 in) optional	0900182/00	3.9 kg (8.6 lbs)
Kit to add mechanical tilt (0° to 10°) to above brackets <i>optional</i>	0900397/00	3.0 kg (6.6 lbs)

Wall mounting brackets are available upon request

INSTALLATION Please read all installation notes before installing this product.



Always attach the antenna by all mounting points.

Do not install the antenna with the connectors facing upwards.

Do not cut the tethered transparent caps(s) that cover the antenna's tilt adjustment indicators.

In order to operate the RET control, the transparent caps covering the tilt adjustment indicators must be engaged and locked.

